CP-1262HE

HDMI to PC/Component Converter with Audio Box

CP-1262HE

● *Disclaimers*

The information in this manual has been carefully checked and is believed to be accurate. Cypress Technology assumes no responsibility for any infringements of patents or other rights of third parties which may result from its use.
Cypress Technology assumes no responsibility for any inaccuracies that may be contained in this document. Cypress also makes no commitment to update or to keep current the information contained in this document.
Cypress Technology reserves the right to make improvements to this document and/or product at any time and without notice.

● *Copyright Notice*

No part of this document may be reproduced, transmitted, transcribed, stored in a retrieval system, or any of its part translated into any language or computer file, in any form or by any means - electronic, mechanical, magnetic, optical, chemical, manual, or otherwise - without express written permission and consent from Cypress Technology.

● *Trademark Acknowledgments*

All products or service names mentioned in this document may be trademarks of the companies with which they are associated.

● Safety Precautions

Please read all instructions before attempting to unpack or install or operate this equipment, and before connecting the power supply. Please keep the following in mind as you unpack and install this equipment:

- ➢ Always follow basic safety precautions to reduce the risk of fire, electrical shock and injury to persons.
- ➢ To prevent fire or shock hazard, do not expose the unit to rain, moisture or install this product near water.
- ➢ Never spill liquid of any kind on or into this product.
- ➢ Never push an object of any kind into this product through module openings or empty slots, as you may damage parts.
- ➢ Do not attach the power supply cabling to building surfaces.
- ➢ Do not allow anything to rest on the power cabling or allow it to be abused by persons walking on it.
- ➢ To protect the equipment from overheating, do not block the slots and openings in the module housing that provide ventilation.

● Revision History

Version No	Date	Summary of Change
VS1	20101201	Add HDCP Description
VR2	20110721	Bi-level Synchronisation

Table of Contents

1. Introduction

This converter box converts digital HDMI to Analog PC or SD/HD output. It enables to connect the HDMI sources to the analog PC monitor, Projector or TV. Its high bandwidth capability supports a wide range of PC and HDTV resolutions.

2. Features

● Supports HDMI input and Analog PC or SD/HD output.

● Supports output selection between YPbPr and RGB.

● Supports input/output resolution as below:

    PC: 640x480= VGA59 , VGA60, VGA72, VGA75, VGA85
        800x600= SVGA56, SVGA60, SVGA72, SVGA75, SVGA85
        1024x768= XGA60, XGA70, XGA75, XGA85
        1152x864= MAC70, MAC75, MAC85
        1280x800= WXGA60
        1280x1024= SXGA60, SXGA75, SXGA85,
        1440x900= WXGA60
        1600x1200= UXGA60
        1680x1050=WSXGA+60
        1920x1200= WUXGA60(pixel-rate=154MHz)
    HD: 480I60, 576I50, 480P60, 576P50, 720P60, 720P50, 1080I60, 1080I50,
        1080P60, 1080P50

    Note: ① As component output at 720p/1080i/1080p needs Tri-level synchronisation in order to allow the image to be display properly. This device supports only bi-level synchronisation and therefore, when output component timing at 720p/1080i/1080p some display may shift to the left side of the screen. This is due to the incorrect start counting point.
   ② If HDMI source includes HDCP(High-bandwidth Digital Content Protection), output display is not supports HDCP decryption and no image will display.

● Built in EDID.

● HDMI 1.3, HDCP 1.1 and DVI compliant.

    Note: This product does not process HDCP input. When receiving content that has HDCp encruption there will be no video output.

3. Operation Controls and Functions

3.1 Front Panel

```
         OUTPUT      HDMI INPUT     DC 5V
         YPbPr
           ┌─┐        ┌──────┐     ┌────┐
    ○      │ │        │      │     │    │    ○
           └─┘        └──────┘     └────┘
           RGB                     ⊖ⓒ⊕

            ①            ②            ③
```

① YPbPr/RGB switch: Set the switch to RGB when your HDMI source equipment is PC graphic card or other digital RGB source signal. Use HD-15 to HD-15 VGA cable to connect between the unit's RGB out and the RGB input of your PC monitor, or projector. Set the switch to YPbPr when your HDMI source equipment is DVD player, set-top-box or other High definition digital video source. Use a VGA to 3 RCA adaptor cable to connect the unit's YPbPr out to the YPbPr input connector of your HDTV.
   Note: When YPbPr output from HD-15 D-Sub the H-pin and V-pin will remain the signal at the same time.
② HDMI input: Connect the HDMI input port to the HDMI output port of your source equipment such as DVD player or set-top-box.
③ Power: Plug the 5VDC power supply into the unit and connect the adaptor to AC wall outlet.

3.2 Rear Panel

```
         PC/YPbPr                   L/R
        ┌───────┐
   ○  ○ │       │ ○            ○  ○
        └───────┘
         ━━━━━━━  OUTPUT  ━━━━━━━

            ①                      ②
```

① HD-15 D-Sub output: Connect the output port to the PC/YPbPr input of analog PC monitor, Projector or TV.
② L/R: Stereo audio output via 3.5mm phone jack.

4. Connection and Installation

Connection 1(RGB out)

HDMI out

or

DVD or, Set-Top-Box

VGA cable

3.5mm to 2 RCA
audio cable

LCD Monitor/TV Projector

DVI out

HDMI cable

DVI to HDMI adaptor

Connection 2 (YPbPr out)

HDMI cable

DVD or, Set-Top-Box

YPbPr cable

D-Sub to 3 RCA cable

Audio

LCD TV

5. HDMI Connector Pin Assignment

Pin#	Function Assignment	Pin#	Function Assignment
1	TMDS Data2+	2	TMDS Data2 Shield
3	TMDS Data2-	4	TMDS Data1+
5	TMDS Data1 Shield	6	TMDS Data1-
7	TMDS Data0+	8	TMDS Data0 Shield
9	TMDS Data0-	10	TMDS Clock+
11	TMDS Clock Shield	12	TMDS Clock-
13	CEC	14	Reserved (N.C. on device)
15	SCL	16	SDA
17	DDC/CEC Ground	18	+5V Power
19	Hot Plug Detect		

Output Format

B. Analog VGA output pin assignment when output switch set to RGB.

C. Analog VGA output pin assignment when output switch set to YPbPr.

Part No.	Pin No.	Description (PC out)
DB15HD	1	RED
	2	GREN
	3	BLUE
	4	GND
	5	GND (DDC-RETURN)
	6	GND-RED
	7	GND-GREEN
	8	GND-BLUE
	9	N.C
	10	GND-SYNC
	11	GND
	12	DDC-DATA
	13	H-SYNC
	14	V-SYNC
	15	DDC-CLOCK

Part No.	Pin No.	Description (HD out)
DB15HD	1	Pr
	2	Y
	3	Pb
	4	GND
	5	GND (DDC-RETURN)
	6	GND-Pr
	7	GND-Y
	8	GND-Pb
	9	N.C
	10	GND-SYNC
	11	GND
	12	DDC-DATA
	13	H-SYNC
	14	V-SYNC
	15	DDC-CLOCK

6. Specifications

Operation Frequency	Up to 225MHz
Input Port	1 x HDMI
Output Ports	1 x HD-15 D-Sub (RGBHV or YPbPr)
	1 x Analog L/R 3.5mm phone jack
Output Signal	RGB: 0.7Vp-p 75ohm
	H/V: 3 to 5 Vp-p
	Or Y: 1 Vp-p 75ohm
	PB/Pr: 0.7 Vp-p 75ohm

Input/Output Resolution PC:

640x480=	VGA59 , VGA60, VGA72, VGA75, VGA85
800x600=	SVGA56, SVGA60, SVGA72, SVGA75, SVGA85
1024x768=	XGA60, XGA70, XGA75, XGA85
1152x864=	MAC70, MAC75, MAC85
1280x800=	WXGA60
1280x1024=	SXGA60, SXGA75, SXGA85,
1440x900=	WSXGA60
1600x1200=	UXGA60
1680x1050=	WSXGA+60
1920x1200=	WUXGA60(pixel-rate=154MHz)

HD: 480I60, 576I50, 480P60, 576P50, 720P60, 720P50, 1080I60, 1080I50, 1080P60, 1080P50

HDMI Audio In	PCM2
HDMI In Color Space	RGB, YUV
Power Supply	5V/1A DC (US/EU standards, CE/FCC/UL certified)
Dimensions (mm)	76(W) x 30(D) x 92(H)
Weight(g)	172
Chassis Material	Aluminum
Silkscreen Color	Silver
Operating Temperature	0°C ~ 40°C
Power Consumption	2.5W (max)

Acronyms

A

Acronym   *Complete Term*